

FLUORESCENT BALLAST SPECIFICATIONS

DESCRIPTION

Model No.	Ballast Type	Starting Type	Qty of Lamps	Lamp Type
BL-13AT5	ELECTRONIC	INSTANT START	1	F8T5, F13T5

ELECTRICAL CHARACTERISTICS

Input Voltage	Frequency	Lamp Watts	Input Watts	Input Current	THD	Power Factor	Sound Rated
120	60Hz	13W	12.3W	<0.19A	<170%	>0.52	A
Min. Starting Temp	Heat Protection Level	Outdoor Type	Open Circuit Voltage	Ballast Frequency	NO PCBS		
0°F/-18°C	CLASS P	TYPE 1	600V	>40KHZ			

PHYSICAL CHARACTERISTICS

	CASE DIMENSIONS					
	Units	M	L	W	H	
	Inch	/	6.07	1	0.79	
	TOL(+/-)	/	0.05	0.05	0.05	
LEAD LENGTH						
Unit	Black	White	Red	Red	Blue	Blue
Inch	11.42	11.42	9.85	11.42	12.21	11.42
TOL(+/-)	+0.5, -0	+0.5, -0	+0.5, -0	+0.5, -0	+0.5, -0	+0.5, -0

BALLAST LABEL

<p>Foshan Innovative Lighting Co.,Ltd Ballast Cat.NO.720 Component E244627 1108 C </p>	<p style="font-size: small;"> Red Tube 8w or 13w T-5 Blue Blue 120v,AC, 60Hz Electronic Ballast Blue Red White Black </p>
--	---

USPAR ENTERPRISES INC.

ADD: 13404 Monte Vista Ave Chino, CA 91710
WEBSITE: www.uspar.com

TEL: 1-909-591-7506
FAX: 1-909-590-3220