



FLUORESCENT BALLAST SPECIFICATIONS

DESCRIPTION

Model No.	Ballast Type	Starting Type	Qty of Lamps	Lamp Type
BL-13SMAG	MAGNETIC	RAPID START	1	PL-13(13W),

ELECTRICAL CHARACTERISTICS

Input Voltage	Frequency	Lamp Watts	Input Watts	Input Current	THD	Power Factor	Sound Rated
120	60Hz	13W	12.6W	<0.35A	<150%	>0.50	A
Min. Starting Temp	Heat Protection Level	Outdoor Type	Open Circuit Voltage	Ballast Frequency	NO PCBS		
0°F/-18°C	CLASS P	TYPE 1	600V	>40KHZ			

PHYSICAL CHARACTERISTICS

	CASE DIMENSIONS						
	Units	M	L	W	H		
	Inch	3.00	2.00	1.88	1.50		
	TOL(+/-)	0.05	0.05	0.05	0.05		
	LEAD LENGTH						
	Unit	Black	Black	Red	Yellow	Green	Blue
	Inch	8	14	/	/	/	/
	TOL(+/-)	+0.5, -0	+0.5, -0	/	/	/	/

USPAR ENTERPRISES INC.

ADD: 13404 Monte Vista Ave Chino, CA 91710
 WEBSITE: www.uspar.com

TEL: 1-909-591-7506
 FAX 1-909-590-3220